

Dear Valued Customer

(JUST WANTED YOU TO KNOW)

**WE REALLY
APPRECIATE
YOUR PURCHASE**

~thank you~

Features

- HDMI 2.0a compliant
- Support MAX resolution 4K@60 4:4:4 8bits
- Support HDR (4K@60 4:2:0 10bits)
- HDCP 2.2, 1.4 compliant
- Support CEC bypass
- Support 7.1 sound

Package contents

- HDMI 2.0 EDID Emulator
- Power adapter DC 5V/1A
- Quick Start Guide

Layout



1. **Micro USB:** Connect to a DC 5V/1A power supply / FW update
2. **LED:** Power indicator
3. **HDMI OUT:** Connect to an HDMI display
4. **HDMI IN:** Connect to an HDMI source
5. **EDID MODE:** See more detail in the DIP SWITCH SETTING section

DIP SWITCH SETTING

Dip Switch (PIN 1) OFF= ↑, ON= ↓	Description
↑	HDMI EDID Mode
↓	DVI EDID Mode

Mode	(PIN 23456) OFF= ↑ ,ON= ↓	Description
1	↑ ↑ ↑ ↑ ↑	EDID Bypass from connected Monitor
2	↑ ↑ ↑ ↑ ↓	EDID Saving*
3	↑ ↑ ↑ ↓ ↓	EDID learning and save to mode2
4	↑ ↓ ↓ ↑ ↑	Full HD(1080p@60) – 8bit 2D video & 7.1ch audio
5	↑ ↓ ↑ ↓ ↓	Full HD(1080p@60) – 8bit 3D video & 2ch audio
6	↑ ↓ ↑ ↓ ↑	Full HD(1080p@60) – 8bit 3D video & 7.1ch audio
7	↑ ↓ ↑ ↑ ↓	HD(1080i@60)(720p@60) – 8bit 2D & 2ch
8	↑ ↓ ↑ ↑ ↑	HD(1080i@60)(720p@60) – 8bit 2D & 7.1ch
9	↑ ↑ ↓ ↓ ↓	Full-HD(1080p@60) – 12bit 2D video & 2ch audio
10	↑ ↑ ↓ ↓ ↑	Full-HD(1080p@60) – 12bit 2D video & 7.1ch audio
11	↑ ↑ ↓ ↑ ↓	Full-HD(1080p@60) – 8bit 2D & 2ch & Dolby 5.1ch

12	↑ ↑ ↓ ↑ ↑	Ultra HD(4K2K@60 4:2:0)-8/10/12bit 3D video & 2ch audio
13	↑ ↓ ↓ ↑ ↓	Ultra HD(4K2K@60 4:2:0) – 8/10/12bit 3D video & 7.1ch audio
14	↑ ↑ ↑ ↓ ↑	Ultra HD(4K2K@60) – 8/10/12bit 3D HDR video & 2ch audio
15	↑ ↓ ↓ ↓ ↑	Ultra HD(4K2K@60) – 8/10/12bit 3D HDR video & 7.1ch audio

*EDID of connected monitor at mode 3 will be save when DIP switch changed from mode 3 to mode 2

Support

For more info or tech support
<http://www.siig.com/support>



HDMI 2.0 EDID Emulator

Quick Start Guide

