## FW Update Instruction

1. Click the tools software of AX6800xIAP\_x64

Press the open files icon to select FW file and click the KVM\_DP14SW0201\_12K(2\_N)V2\_1\_0-20210308-17-53.bin

文件夹		
名称 🔺	Vendor ID (Hez)	Status
🕺 AX6800xIAP_x64. exe	Product ID (Hez) 6800	
History. txt	AX6800x Firmware Download Setting	
KVM_DP14SW0201_12K(2_N)V2_1_0-20210308-17-53. bin	O Download KVM system Code	
🜌 setup. dat	C Download Bootloader Code	
	🖸 Download Software Config	
	▶E:\My_Work\2019┽\KVM-DP14SW0201-M\FW_长按开关热键版FW\KVM-	
	Result: Download	
	Connect	
	Time Cost: 00:00:00	

2. Plug-in the power adapter to the DC jack, connect the PC to USB PC2 port.

2x1 DisplayPort Switch photo

	HDMI Out	LipiayPort Out	DisplayPort in	PC1	PC2	DC 5V
				Connect	to P	C

3. Hold the PC1 button and then press the power button, until the green light flashing from Online.



4. Click the "connect" first, and then click the Download when appears the "disconnect".

T AX6800xIAP Ver.1.0.0		_ 🗆 🗙
Vendor ID (Hez) 0595	Status	
Product ID (Hez) 6800	Disconnect device	<u> </u>
AX5800x Firmware Download Setting		
O Download KVM system Code		
🔿 Download Bootloader Code		
C Download Software Config		
late_FW\KVM_DP14SW0201_12K(2_N)V2_1_0=2020=11=09=18=21. bin		
Result:		
Comiosd.		
Connect		
		~
Time Cost: 00:00:00		



5. When the result appears the green circle has been completed;

TAX6800xIAP Ver.1.0.0		_ 🗆 🗡
Vendor ID (Hem)	Status	
Product ID (Hemma 6800	Start to transmit Runtime firmware to AX6800x device	<b></b>
AX5800x Firmware Download Setting	Runtime file is loaded. File size: 104250 bytes.	
💿 Download KVM system Code	Chip Revision : 1	
🔿 Download Bootloader Code	Runtime firmware is transmitted successfully	
C Download Software Config	Device Unpluged	
late_FW\KVM_DP14SW0201_12K(2_N)V2_1_0=2020=11=09=18=21.bir		
Result: Download		
Connect		
		_
	J	Y
Time Cost: 00:00:00		